

# AM-30D/AM-60D

## 30W/60W Class-D Mixer Amplifier



### Features:

- Rated power 30W/60W
- Speaker output: 70V/100V & 4-16Ω
- Built-in Class-D amplifier module, high efficiency (85%)
- With USB, FM and Bluetooth function
- AUX 1-2 input of RCA interface and one RCA line output
- Mic 1 with priority & phantom power 24V
- Protection: Overload, Short circuit, Overheat, Clip
- Power supply: AC110V-240V/50Hz/60Hz

### Specification:

Model	AM-30D	AM-60D
Rated Power	30W	60W
Power Supply	AC~110-240 50/60Hz	
Output	4-16 ohm 70V /100V	
Frequency Response	80HZ-20KHZ	
S/N Ratio	75 dB	
Distortion	<0.5% at 1KH2 100V -3dB	
Interface Output Model	1-8mV	
AUX Input Sensitivity	AUX1-2 500mV/10Kohm	
MIC Input Sensitivity	M1C1-2 1-6mv	
Treble Adjustment	10kHz +-10dB	
Bass Adjustment	100Hz +-10dB	
DIMENSIONS	210MM*44MM*220mm(W*H*D)	
Weight	3kg	3.5kg

Suitable for small spaces of approximately 20–80 m<sup>2</sup>, including small shops, commercial spaces, residential/home areas, small public places, foot spas, beauty salons and barbershops.