



MP-460/MP-4120/MP-4180

60W/120W/180W 4 Zones Mixer Amplifier



Features:

- Rated Power: 60W/120W/180W
- Speaker output: 70V/100V & 4-16 Ω speaker output
- Input source: 2 MIC, 3 AUX and USB/FM/Bluetooth (5.0 Version)
- Support power-off memory playback.
- 4 unit signal indicators, protection light indication.
- With treble and bass control and master volume control.

Specification:

Model	MP-460	MP-4120	MP-4180
Rated Power	60W	120W	180W
Power Supply	AC~110-220V 50/60Hz		
Output	4-16 ohm 70V /100V		
Frequency Response	80HZ-20KHZ		
S/N Ratio	75 dB		
Distortion	<0.5% at 1KH2 100V -3dB		
Interface Output Model	1-8mV		
AUX Input Sensitivity	AUX1-2 500mW/10Kohm MIC1-3 1-6MV		
Treble Adjustment	10kHz +-10dB		
Bass Adjustment	100Hz +-10dB		
DIMENSIONS	460MM*66MM*230mm(W*H*D)		
Weight	7kg	11kg	13.5kg

Suitable for small to medium-sized spaces up to **240–720 m²** that require four-zone independent volume control, such as hotels, resorts, restaurants, cafes, entertainment lounges office buildings, conference centers, showrooms, shopping malls, retail stores, supermarkets schools, kindergartens, training centers, waiting areas, community centers, libraries, office parks

back

source: www.aiship.com