



# MP-6120S/MP-6250S/MP-6350S/MP-6450S/MP-6550S

## 120W-550W 6 Zones Mixer Amplifier with MP3/USB/BT/SD/ECHO/AUX



### Features:

- 6zones speaker output,each zone with individual volume control
- 3MICinputs, Mic 1 with priority and echo function
- 2AUXline input & 1 AUX line output for power extension
- Each AUX&Mic input with individual volume control
- Bass & Treble tone control for better sound quality control
- 100V &4-16Ω optional speaker output for different uses
- Built with chime, emergency evacuation, alarm sound
- Support DC24V fire strong cut input to trigger alarm sound
- Support MP3/FM/SD/Bluetooth version 5.0(Distance 10m)
- Protection of overload, overheating, over-current, etc.,

### Specification:

Model	MP-6120S	MP-6250S	MP-6350S	MP-6450S	MP-6550S
Rated Power	120W	250W	350W	450W	550W
Speaker Output	100V & 4-16 Ω				
Input A/C power	AC210-240V 50Hz				
A/C Fuse	4A	5A	6.3A	8A	12A
70v Output	33.5 Ω	20 Ω	14 Ω	11 Ω	8.5Ω
100v Output	67Ω	40Ω	28.5Ω	22Ω	17Ω
Frequency Response	20KHz -60Hz <-1dB>				
THD	100VOUT<-3dB> 0.5%				
AUX INPUT	300mV				
MIC INPUT	4mV				
S/N Ratio	>80dB				
PEC OUT	650mV-750mV				
Dimension:	483mmx88mmx320mm				
Weight:	12KG	13.5KG	14.5KG	17.5KG	20.5KG

Suitable for medium to large commercial and public spaces that require 6-zone independent volume control, such as schools, universities, auditoriums and lecture halls, hospitals, clinics and waiting areas, restaurants, entertainment venues, conference rooms, multi-function halls and exhibition centers