

MA-6120/MA-6250/MA-6350/MA-6450/MA-6550

60W/ 120W/ 250W/ 350W/ 450W/ 550W 6 Zone Mixer Amplifier with Siren



Features:

- Rated power:
120W/250W/350W/450W/550W
- Speaker output: 70V/100V & 4-16 Ω speaker output
- Input source: 3 Mic Echo, 2 Aux, Pre-out
- MIC1 has a priority function, with reverberation function
- With treble bass adjustment control.
- 6 zone output, independent volume control for each zone
- Bring alarm triggering switch, support DC24V fire strong cut input trigger alarm sound.
- Indicator light for overload, overheating, over-current ,protection function.
- Support 4 remote control Mic

Specification:

Model	MA-6120	MA-6250	MA-6350	MA-6450	MA-6650
OUTPUT POWER	120W	250W	350W	450W	550W
POWER INPUT	110V-220V AC 50-60HZ				
FREQUENCY RESPONSE	80HZ-20KHZ				
DISTORTION(THD)	<0.5% at 1KHZ 100V -3dB				
Output Voltage	4-16ohm 70V 100V				
AUX/MIC	AUX1-2 500mV/10Kohm/MIC1-3 1-6mV				
S/N	75dB				
TONE CONTROL	Bass:100Hz-+10dB Treble:10kHz-+10dB				
DIMENSIONS	485*88*340mm(W*H*D)				
WEIGHT	11KG	13.5KG	14.5KG	16.5KG	17.5KG

Suitable for medium to large places that require 6-zone independent control, background music, paging and emergency siren alarm, such as schools, universities, auditoriums and lecture halls, hospitals, clinics and waiting areas, restaurants, entertainment venues, conference rooms, multi-function halls and exhibition centers

exhibition centers