

DM-6120R/DM-6250R/DM-6350R/DM-6450R/DM-6550R

6 ZONES MIXER AMPLIFIER WITH PAGING STATION



Features:

- Rated Power: 120W/250W/350W/450W/550W
- Speaker output: 70V/100V & 4-16 Ω speaker output
- Input source: 6 Mic, 3 AUX and USB/FM/Bluetooth/TF
- Support 6 zone remote paging MIC, up to 4 pcs
- With 19" rack mount handles
- Individual volume control and Bass/Treble adjustment
- MIC1 has the priority function
- Mute and Alarm, support short circuit triggers
- Playing and storing 6 song files, short circuit triggers playback of songs
- Protection: Overload, Clipping, Short circuit and temperature protection

Specification:

Model	DM-6120R	DM-6250R	DM-6350R	DM-6450R	DM-6650R
OUTPUT POWER	120W	250W	350W	450W	650W
POWER INPUT	110V-220V AC 50-60HZ				
FREQUENCY RESPONSE	80HZ-20KHZ				
DISTORTION(THD)	<0.5% at 1KHZ 100V -3dB				
Output Voltage	4-16ohm 70V 100V				
AUX/MIC	AUX1-2 500mV/10Kohm/MIC1-3 1-6mV				
S/N	75dB				
TONE CONTROL	Bass:100Hz+10dB Treble:10kHz+10dB				
DIMENSIONS	485~88-340mm(W*H*D)				
WEIGHT	11KG	13.5KG	14.5KG	16.5KG	17.5KG

Perfect for background music, zone BGM, emergency announcements, paging calls and public address system which are medium to large public & commercial places, such as schools, universities, auditoriums and lecture halls, hospitals, clinics and waiting areas, restaurants, entertainment venues, conference rooms, multi-function halls and exhibition centers

rooms, multi-function halls and exhibition centers