



MA-60/MA-120

60W/120W Class-D MIXER AMPLIFIER



Features:

- Multiple audio input: USB/FM/Bluetooth/SD Card/Remote Controller
- 4-16ohm, 70v-100v speaker output, Mute function
- 2 MIC input, Mic1 has the priority and phantom power
- 2 AUX input, bass and treble adjustment, master control
- Best choice for some small-medium places, such as coffee shops, small restaurants, small department store, hair salons, classrooms etc.,

Specification:

Model	MA-60	MA-120
Rated Power	60W	120W
Power Supply	AC~110-240 50/60Hz	
Output	4-16 ohm 70V /100V	
Frequency Response	80HZ-20KHZ	
Distortion	<0.5% at 1KH2 100V -3dB	
Interface Output Model	1-8mV	
AUX Input Sensitivity	AUX1 500mW/10Kohm	
MIC Input Sensitivity	M1C1-2 1-6mv	
Treble Adjustment	10kHz +-10dB	
Bass Adjustment	100Hz +-10dB	
DIMENSIONS	250MM*70MM*240mm(W*H*D)	

Suitable for small spaces of approximately 20–80 m², including small shops, commercial spaces, residential/home areas, small public places, foot spas, beauty salons and barbershops.

09196121062*