



WA-120F/WA-240F/WA-350F

6 zones WiFi Amplifier with USB/FM/AUX/Phantom Power



Features:

- 120W/240W/350W power outputs available
- Support:USB,BTFM,DAB+,Aux In
- Mic 1has priority over the other inputs
- 70/100V and 4/8 ohms(Ω)output loads
- 2 groups of Aux inputs,1 group of Aux outputs
- 70V or 100V speaker outputs with separate switch ON/OFF
- Five 48V Phantom Power and four 6.35mm microphone jacks
- HD display for the working status of playing program
- Built-in Chime and Siren with push-button and volume control
- BASS and TREBLE tone controllers
- Individual LED indicator for POWER/SIGNAL/PROTECTION
- Removable rack mounting brackets supplied
- Complete protection for short circuit,overload,high temperature

Application Scenario	Recommended Power	Key Advantages
Small Retail Stores / Classrooms / Home Use	120W / 240W	Compact size, low power consumption, ideal for small-space audio reinforcement
Medium-sized Malls / Hotels / Conference Rooms	350W / 480W	Multi-zone & multi-audio-source support, perfect for medium-sized spaces

Specification:

Model	MA-120F	MA-240F	MA-350F
Rated power	120W	240W	350W
Speaker output mode	70V/100V 4 & 8 ohms(Ω)		
WiFi Solution	Legacy Wireless Hi-fi System		
WiFi APP Name	Legacy Player		
WiFi APP Version	Android, ios		
Wi-Fi Mode	Wi-Fi 8.2.11 b/g/n(AP/STA modes supported)		
Music Format	Supported with MP3,WMA,ACC(ACC+)Apple lossless,ALAC,FLAC,APE,WAV		
Frequency Response	60 Hz ~ 15k Hz (\pm 3 dB)		
T.H.D	<1% at 1kHz,1/3 rated power		
S/N	\geq 75dB		
Tone Control	BASS:100 Hz (+ 10 dB), TREBLE:10k Hz (\pm 10 dB)		
Audio input	MIC,AUX, USB, BT, WIFI		
Protection	Short circuit,overload,high temperature		
AC Fuse	T2A	T4A	T4A
Power supply	AC 220-240V- 50/60Hz		
Power consumption	264W	528W	770W
Power cord	(3x0.75 mm)x1.5M		
Dimension (HxWxD)	100x430x340mm	100x430x340mm	100x430x340mm
Carton size(HxWxD)	185x520x435mm	185x520x435mm	185x520x435mm
Net weight	8.45kgs	12.50kgs	12.70kgs
Gross weight	9.70kgs	13.90kgs	14.10kgs