



MP-260/MP-212/MP-218 60W/120W/180W 2 zones Mixer Amplifier with USB/BT/FM/AUX/SD



Features:

- Rated power 60W/120W/180w
- Speaker output: 70V/100V & 4-16Ω
- 2 MIC input, 2 AUX input
- 2 zones with in-dependant adjustment
- LCD display screen, support USB / SD / FM / BT 5.0
- Support power-off memory playback.
- 4 unit signal indicators, protection light indication.
- With treble and bass control and master volume control.

Specification:

Model	MP-260	MP-212	MP-218
Rated Power	60W	120W	180W
Power Supply	AC~110-220V 50/60Hz		
Output	4-16 ohm 70V /100V		
Frequency Response	80HZ-20KHZ		
S/N Ratio	75 dB		
Distortion	<0.5% at 1KH2 100V -3dB		
Interface Output Model	1-8mV		
AUX Input Sensitivity	AUX1 500mW/10Kohm		
Treble Adjustment	10kHz +-10dB		
Bass Adjustment	100Hz +-10dB		
DIMENSIONS	240MM*88MM*220mm(W*H*D)		
Weight	9kg	11kg	13kg

Ideal for 50–250 m² mid-sized spaces, such as Retail stores, supermarkets, restaurants, cafes, hotels, offices, meeting rooms, showrooms, schools, classrooms, training centers, Beauty salons, gyms

